Product data sheet

Specifications



NEMA Motor Starter, Type S, replacement coil, 110/120VAC 50/60Hz, 2 or 3 pole, NEMA Size 2 starter and 8903SP lighting

3106340938

Product availability: Stock - Normally stocked in distribution facility

Main

Product or Component Type	Coil
Accessory / separate part destination	Class 8502 type SD contactor Class 8903 type SP lighting contactor

Complementary

NEMA size	2
[Ue] rated operational voltage	120 V AC 60 Hz 110 V AC 50 Hz
Inrush power in VA	296 VA 311 VA
Average consumption	36 VA 37 VA
Height	2.6 in (66.2 mm)
Width	4.0 in (101.1 mm)
Depth	2.4 in (61.7 mm)

Ordering and shipping details

Category	US10CP118061
Discount Schedule	0CP1
GTIN	785901484882
Returnability	Yes
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.600 in (6.604 cm)
Package 1 Width	2.500 in (6.350 cm)
Package 1 Length	4.000 in (10.160 cm)
Package weight(Lbs)	12.480 oz (353.802 g)

Contractual warranty

Warranty (in months)	18

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No

Use Longer

Lifetime extension

Repair	No

Use Again

Repack and remanufacture

Take-back	No